

**LQ1260 SERIES DIGITAL CLOCK INSTALLATION NOTES**  
THANK YOU FOR PURCHASING THIS DIGITAL CLOCK FROM CRUISING ELECTRONICS

**INSTALLATION NOTES**

This clock is designed for operation from a 12 volt DC source only (9 to 16v)

Allowable ambient temperature range -20 to + 50° C

The display type is designed for indoor use, eg bedside use, it is not designed to be readable in full sunlight

You will note there are two + power wires (plus negative of course).

If you connect them together, then to the 12 volt source (via a fuse, and switch), the clock will turn off and lose it's time setting when the switch is opened or the power removed from the clock in any other way.

If you connect the RED wire separately to a permanent 12 volt source, and the ORANGE wire via a switch, the clock display will go off when you open the switch, but the clock will retain it's time memory because of the permanent voltage on the RED wire.

Whilst this seems a good idea, just bear in mind the memory function will draw a very small amount of power from your batteries, about 10mA or 100<sup>th</sup> of an amp.

If laying the camper/boat up for a long period, say over winter, we recommend disconnecting the clock

As usual best practise, please ensure all + wiring is fused as near as possible to the voltage source and run in a workmanlike manner. All connections must be secure, low resistance and protected.

In-line fuses would be fine, use a rating of ½ or 1 amp

Some models are supplied with a housing to enable flush mounting into a bulkhead.

To fit into a bulkhead the housing requires a cut-out of 70mm x 32mm (2.75" x 1.26").

Firstly, carefully remove the clock from the housing, taking care not to apply undue tension to the rear cable.

Fit the housing in the cut-out, then use the supplied double sided tape to fix the clock securely back into the housing.

**OPERATION**

This is a 12 hour clock. There is a PM indication in the top LH corner. The centre colons flash at 1 second intervals

- >> Press to set the hours, or advance the display rapidly, depending on the model
- > Press to set the minutes, or advance the display slowly, depending on the model

**WARRANTY**

**In the event of malfunction or failure Cruising Electronics will, at their sole discretion, either repair or replace the unit, providing that:**

Malfunction has occurred within 12 months from the date of purchase

Any or all of the listed ratings of the unit have not been exceeded

The unit has been properly installed, with regard to correctly rated cables, fuses, switches and any other ancillary items which could reasonably be regarded as necessary to effect a safe and workmanlike installation. Any factory seals must be intact.

The unit has not been exposed to any fluid, corrosive or hazardous substance, excessive airborne particles

The unit is returned freight paid to Cruising Electronics or their nominated agent

Proof of purchase is provided

**Please note that under no circumstances can Cruising Electronics be held liable or accept liability for any consequential damages or loss whatsoever, incurred as a result of installing or operating this clock.**

**CRUISING ELECTRONICS  
67 WELLINGTON STREET  
RUSSELL 0202  
NEW ZEALAND  
TELEPHONE 027 2552852 (+64 27 2552852)  
don@cruisingelectronics.com  
www.cruisingelectronics.com**